



NeoSpectra™ SWS62231 – Java SDK Developers Guide

Information in this document is provided in connection with Si-Ware Systems products. These materials are provided by Si-Ware Systems as a service to its customers and may be used for informational purposes only. Si-Ware Systems assumes no responsibility for errors or omissions in these materials. Si-Ware Systems may make changes to its products, specifications, and product descriptions at any time, without notice. Si-Ware Systems makes no commitment to update the information and shall have no responsibility whatsoever for conflicts, incompatibilities, or other difficulties arising from future changes to its products and product descriptions. No license, express or implied, by estoppels or otherwise, to any intellectual property rights is granted by this document. Except as may be provided in Si-Ware Systems' Terms and Conditions of Sale for such products, Si-Ware Systems assumes no liability whatsoever.

Copyright

Copyright © 2020 Si-Ware Systems. All rights reserved.
The information in this document is proprietary to Si-Ware Systems, and for its customers' internal use. In any event, no part of this document may be reproduced or redistributed in any form without the express written consent of Si-Ware Systems.

Contacts

For technical assistance, please contact:

Si-Ware Systems
3, Khaled Ibn Al-Waleed St.
Sheraton, Heliopolis
Cairo 11361, Egypt

Tel.: + 20 222 68 47 04
Email: neospectra.support@si-ware.com

Trademarks

NeoSpectra™ and SpectroMOST™ are trademarks of Si-Ware Systems

Contents

JAVA SDK GUIDE	4
CHAPTER 1 SDK	5
1. <i>Installation</i>	5
2. <i>Software Architecture</i>	5
3. <i>APIs</i>	6
4. <i>Sequence diagrams</i>	17

Java SDK Guide

Chapter 1 SDK

1. Installation

SpectroMOST Micro should be installed before proceeding with the SDK installation steps.

After downloading the SDK package the following steps should be performed in Eclipse IDE:

1.1. Opening Project:

Apply the following steps:

1. Click File → New → Project → Java Project.
2. Brows to your SDK folder location.
3. In source tab:
 - Make sure that you've 2 folders marked as source folders (spectromost_micro/src, release)
 - In case not all of the previous folders were marked as source folders, right click on that folder and select "Use as source folder".
 - Ensure that the "Default output folder" field contains the path to the bin folder.
4. Press finish.

1.2. Run configuration:

In the run configuration window apply the following steps:

1. Java Application → new configuration.
2. In main tab: main class → search for(Userinterface).
3. In argument tab :
 - VM arguments: write the following command:
-Djava.library.path="bin_path_inside_SDK_folder"
-Dswing.defaultlaf=com.sun.java.swing.plaf.nimbus.NimbusLookAndFeel
 - Working directory → \${workspace_loc:SDK_MOST/bin}

2. Software Architecture

SpectroMOST Micro application has the components described below.

1. Application software
 - spectromost.jar: The source code of SpectroMOST Basic Edition is delivered as for reference. This component should be replaced by the end-use application software.
 - 3rd party modules used by spectromost.jar:
 - jcommon-1.0.21.jar
 - jfreechart-1.0.17.jar
 - log4j-1.2.17.jar
 - miglayout15-swing.jar
2. Spectrometer driver:
 - p3AppManager_micro.jar (which is the only component from which spectromost.jar calls the different APIs)

3. APIs

p3AppManager_micro APIs

The p3AppManager component has the following APIs:

1. Interface: p3AppManagerImpl()

Description: Component Constructor

Inputs	Outputs	Return	Type
String dir (optional): Set the working directory of the SDK.	-	-	Sync

2. Interface: addObserver()

Description: Add the caller as an observer in the p3AppManager

Inputs	Outputs	Return	Type
Reference to the caller instance.	-	-	Sync

Notes:

- Guidelines to get the status of the software:
 - Your class should implement “Observer” interface.
 - The class should add itself as an observer to “p3AppManager” class through addObserver() method.
 - Update() method will be invoked from p3AppManager once an action has been finished. This method should be overridden also in your class.

3. Interface: getDeviceId()

Description: Gets the ID of the connected spectrometer module.

Inputs	Outputs	Return	Type
-	String deviceId	Spectrometer ID	Sync

4. Interface: initializeCore()

Description: Begin initializing the connected board

Inputs	Outputs	Return	Type
-	-	p3AppManagerStatus: See Table 3	Async

5. Interface: runSpec()

Description: Generate Spectrum (relative to background measurement)

Inputs	Outputs	Return	Type
- String runTime: Scan time in milliseconds - isSample: false means	-	p3AppManagerStatus: See Table 3	Async

background and true means sample - String apodization (optional) - String zeroPadding (optional) - String gainValue - String NumberOfDataPoints See Table 1 - String continues mode: Set by 1 if continues run is taken and set by zero if single run is taken			
---	--	--	--

6. Interface: getSpecData()

Description: Get data corresponding to runSpec function

Inputs	Outputs	Return	Type
-	See Table 2	double[][]	Sync

7. Interface: runInterSpec()

Description: Generate Interferogram and Power Spectral Density

Inputs	Outputs	Return	Type
- String runTime: Scan time in milliseconds - String apodization (optional) - String zeroPadding (optional) - String gainValue - String NumberOfDataPoints See Table 1 - String continues mode: Set by 1 if continues run is taken and set by zero if single run is taken	-	p3AppManagerStatus: See Table 3	Async

8. Interface: getInterSpecData()

Description: Get data corresponding to runInterSpec command

Inputs	Outputs	Return	Type
-	See Table 2	double[][]	Sync

9. Interface: checkDeviceStatus()

Description: Check the current status of the connected device

Inputs	Outputs	Return	Type
-	-	p3AppManagerStatus:	Sync

		See Table 3	
--	--	-------------	--

10. Interface: wavelengthCalibrationBG()

Description: Perform first step of the wavelength calibration using background reading

Inputs	Outputs	Return	Type
<ul style="list-style-type: none"> - String runTime: Scan time in milliseconds - String apodization (optional) - String zeroPadding (optional) See Table 1 <ul style="list-style-type: none"> - String gainValue - String NumberOfDataPoints 	-	p3AppManagerStatus: See Table 3	Async

11. Interface: wavelengthCalibration()

Description: Perform second step of the wavelength calibration using a known calibrator (sample)

Inputs	Outputs	Return	Type
<ul style="list-style-type: none"> - String runTime: Scan time in milliseconds - String calibrator Type: name of the sample to be used - String apodization (optional) - String zeroPadding (optional) See Table 1 <ul style="list-style-type: none"> - String gainValue - String NumberOfDataPoints 	-	p3AppManagerStatus: See Table 3	Async

12. Interface: runSpecGainAdjBG()

Description: Add a new gain for the spectrum using background

Inputs	Outputs	Return	Type
<ul style="list-style-type: none"> - String runTime: Scan time in milliseconds 	-	p3AppManagerStatus: See Table 3	Async

13. Interface: getGainAdjustSpecData()

Description: Get gain settings corresponding to runSpecGainAdjBG()

Inputs	Outputs	Return	Type
-	-	double[][]	Sync

14. Interface: burnSpecificSettings()

Description: Burn specific gain settings and enable/disable the saving of the wavenumber correction values on the module

Inputs	Outputs	Return	Type
<ul style="list-style-type: none"> - String [] settingsToBurn: List containing the name of the gain settings to burn - String updateCorrection: flag if set to true it saves the correction values to the module. 	-	p3AppManagerStatus: See Table 3	Async

15. Interface: restoreDefaultSettings()

Description: Restore the default gain settings and wavenumber correction settings from the module

Inputs	Outputs	Return	Type
-	-	p3AppManagerStatus: See Table 3	Async

16. Interface: setWorkingDirectory()

Description: Sets the working directory of the application

Inputs	Outputs	Return	Type
<ul style="list-style-type: none"> - String dir: Path to the working directory 	-	-	Async

17. Interface: getWorkingDirectory()

Description: return the current working directory of the application

Inputs	Outputs	Return	Type
-	-	- String : Path to the working directory	Async

18. Interface: setExternalApodizationWindow()

Description: Sets the Apodization window with an external window from the user.

Inputs	Outputs	Return	Type
<ul style="list-style-type: none"> -Long[] apodizationWindow: External window defined by user 	-	-	Async

19. Interface: getSoftwareVersion()

Description: Return the software version number

Inputs	Outputs	Return	Type
-	-	- String : Software version number	Async

Input Data Format

Parameter	Description	Value	Description
Apodization	Shape of the window to be used to multiply the Interferogram before FFT	Boxcar	
		Gaussian	
		Happ-Genzel	
		Lorenz	
ZeroPadding	Number of points to be added to the Interferogram before FFT	0	No points to add
		1	1*VALUE= number of points to add
		3	3*VALUE= number of points to add
OpticalGainPrefix	Identifier between Interferogram gain settings and Spectrum gain settings	_InterSpec_	To retrieve the gain in case of background or interferogram
		Spec	To retrieve the gain in case of Sample
NumberOfDataPoints		65 pts	
		129 pts	
		257 pts	
		513 pts	
		1024 pts	
		2048 pts	
		4096 pts	

Table 1: Input data format

Output Data Format

Two-dimensional array holds the spectrum/interferogram data which consists of the following arrays:

API Name	Array Index	Description	Data Set	Axis	Units
getInterSpecData()	0	Optical path difference values	Interferogram	X	µm
	1	Photo detector's current intensity values (Interference pattern)	Interferogram	Y	nA
	2	Wavenumber values	Spectrum	X	cm-1

	3	Power density spectral values (PSD)	Spectrum	Y	a.u.
getSpecData()	2	Wavenumber values	Spectrum	X	cm-1
	3	Absorbance values (relative to background measurement)	Spectrum	Y	Abs.

Table 2: Input data format

p3AppManagerStatus

Statu s Code	Enum	Message
0	<i>NO_ERROR</i>	No error
1	<i>DEVICE_BUSY_ERROR</i>	Device is busy.
2	<i>BOARD_DISTCONNECTED_ERROR</i>	SpectroMOST does not detect any connected NeoSpectra module
3	<i>BOARD_NOT_INITIALIZED_ERROR</i>	NeoSpectra module is not initialized
4	<i>UNKNOWN_ERROR</i>	Unknown error. Contact Si-Ware Systems
7	<i>CONFIG_FILES_LOADING_ERROR</i>	Error in loading resolution folder
8	<i>CONFIG_PARAM_LENGTH_ERROR</i>	Error in resolution folder format
11	<i>INVALID_RUN_TIME_ERROR</i>	Invalid scan time
23	<i>INVALID_REG_FILE_FORMAT_ERROR</i>	Error in resolution folder format
24	<i>NO_OF_SCANS_DSP_ERROR</i>	DSP error
25	<i>DSP_INTERFEROGRAM_POST_PROCESSING_ERROR</i>	DSP error
26	<i>DSP_INTERFEROGRAM_POST_EMPTY_DATA_ERROR</i>	DSP error
27	<i>DSP_INTERFEROGRAM_POST_BAD_DATA_ERROR</i>	DSP error
28	<i>UPDATE_CORR_FILE_ERROR</i>	Error updating resolution folder
29	<i>WHITE_LIGHT_PROCESSING_ERROR</i>	Error in saving background data
30	<i>DSP_INTERFEROGRAM_FFT_POST_PROCESSING_ERROR</i>	DSP error
31	<i>INVALID_RUN_PARAMETERS_ERROR</i>	Invalid run parameters
32	<i>INVALID_RUN_TIME_NOT_EQUAL_BG_RUN_TIME_ERROR</i>	Background measurement scan

		time is not equal to sample measurement scan time
33	<i>NO_VALID_BG_DATA_ERROR</i>	No valid background measurement found
34	<i>INTERFERO_FILE_CREATION_ERROR</i>	Error occurred during saving interferogram data
35	<i>PSD_FILE_CREATION_ERROR</i>	Error occurred during saving PSD data
36	<i>SPECTRUM_FILE_CREATION_ERROR</i>	Error occurred during saving spectrum data
37	<i>GRAPHS_FOLDER_CREATION_ERROR</i>	Error occurred during creating data folder
38	<i>INVALID_APODIZATION_WINDOW</i>	Error occurred while loading an invalid apodization window number
42	<i>INITIATE_MIPDRIVER_ERROR</i>	Error occurred during NeoSpectra module initialization
43	<i>INVALID_BOARD_CONFIGURATION_ERROR</i>	Error occurred during NeoSpectra module initialization
50	<i>DATA_STREAMING_TAIF_ERROR</i>	Error occurred during streaming from NeoSpectra module
51	<i>DATA_STREAMING_ERROR</i>	Error occurred during streaming from NeoSpectra module
52	<i>INVALID_NOTIFICATION_ERROR</i>	Error occurred during result return
53	<i>INVALID_ACTION_ERROR</i>	Invalid action performed
54	<i>INVALID_DEVICE_ERROR</i>	Invalid device is attached
55	<i>THREADING_ERROR</i>	Threading error occurred
60	<i>ACTUATION_SETTING_ERROR</i>	Error occurred during the setup of actuation settings
61	<i>DEVICE_IS_TURNED_OFF_ERROR</i>	NeoSpectra module is switched off
62	<i>ASIC_REGISTER_WRITING_ERROR</i>	Error occurred during writing to chip registers
110	<i>FAILED_IN_ADAPTIVE_GAIN</i>	Error occurred while save gain settings
111	<i>ASIC_REGISTER_READING_ERROR</i>	Error occurred during ASIC register reading
116	<i>WAVELENGTH_CALIBRATION_ERROR</i>	Calibrator has no wavelengths in the detector range
117	<i>NO_VALID_OLD_MEASUREMENT_ERROR</i>	Error occurred while there is no old

		measurement found
118	<i>DSP_UPDATE_FFT_SETTINGS_ERROR</i>	Error while make DSP data update FFT settings
199	<i>USBCommunicationTimeOutError</i>	Error occurred during USB communication
201	<i>CommunicationWriteError</i>	Error occurred during TAIF writing register
202	<i>CommunicationReadError</i>	Error occurred during TAIF reading register
203	<i>FLASHING_CONFIGURATION_ERROR</i>	Error occurred during flash the program
213	<i>ROM_INVALID_ID</i>	sample ID isn't correct
214	<i>DEVICE_NOT_INITIALIZED_ERROR</i>	Error occurred if device is not initialized
218	<i>SAMPLE_FOLDERS_INVALID_ERROR</i>	Error occurred if sample folder is not supported
228	<i>OPTICAL_FILE_ERROR</i>	Error occurred during optical sittings
229	<i>NOT_ENOUGH_MEMORY_ERROR</i>	Not enough memory error
230	<i>I2_STAT_INT1_END_TIMEOUT</i>	ASIC returned error during interpolation from block1
231	<i>I2_STAT_INT1_END_INVALID</i>	ASIC returned error during interpolation from block1
232	<i>I2_STAT_INT1_AVG_OVERFLOW</i>	ASIC returned error during interpolation from block1
233	<i>I2_STAT_INT1_CORE_INVALID_REGION</i>	ASIC returned error during interpolation from block1
234	<i>I2_STAT_INT1_CORE_TIMEOUT</i>	ASIC returned error during interpolation from block1
235	<i>I2_STAT_INT1_CORE_OVERFLOW</i>	ASIC returned error during interpolation from block1
236	<i>I2_STAT_INT1_START_TIMEOUT</i>	ASIC returned error during interpolation from block1
237	<i>I2_STAT_INT2_END_TIMEOUT</i>	ASIC returned error during interpolation from block2
238	<i>I2_STAT_INT2_END_INVALID</i>	ASIC returned error during interpolation from block2
239	<i>I2_STAT_INT2_AVG_OVERFLOW</i>	ASIC returned error during interpolation from block2
240	<i>I2_STAT_INT2_CORE_INVALID_REGION</i>	ASIC returned error

		during interpolation from block2
241	<i>I2_STAT_INT2_CORE_TIMEOUT</i>	ASIC returned error during interpolation from block2
242	<i>I2_STAT_INT2_CORE_OVERFLOW</i>	ASIC returned error during interpolation from block2
243	<i>I2_STAT_INT2_START_TIMEOUT</i>	ASIC returned error during interpolation from block2
244	<i>INVALID_SAMPLE_FOLDER_VERSION</i>	Version number of sample folder isn't supported
245	<i>TAIF_STREAMING_ERROR_INT1</i>	
246	<i>STREAMING_TIMEOUT_ERROR</i>	Error due to timeout of the streaming interpolation data
247	<i>TAIF_STREAMING_ERROR_INT2</i>	
248	<i>P3_FFT_ADDRESS_ERROR</i>	Error occurred during reading FFT address memory
300	<i>FFT_WRONG_NUMBER_POINTS</i>	FFT number of points is not supported
249	<i>CRC_NOT_MATCHED</i>	Error occurred during check the program correctness
250	<i>PATTERN_NOT_MATCHED</i>	Error occurred during pattern is not matched
251	<i>FLASH_FAILED</i>	Error occurred while writing on flash, no more pages in flash memory
252	<i>IN_ADDRESS_ERROR</i>	Error occurred in flash address
253	<i>RX_OR_ERROR</i>	Error occurred in Flash SPI slave block
254	<i>WRITE_ENABLE_FAILED</i>	Write enable command to flash is failed
255	<i>WRITE_DISABLE_FAILED</i>	Write disable command to flash failed
256	<i>FLASH_BUSY_ERROR</i>	Flash is not responding
259	<i>P3_SPI_TAIF_ADDRESS_ERROR</i>	Error in TAIF Register address to be written or read
204	<i>P3_SPI_TAIF_RX_OR_ERROR</i>	Receive overrun flag (asserted when new operation is started before the previous data received from single access operation is read,

		cleared by reading this register)
250	<i>P3_SPI_TAIF_IN_ADDR_ERROR</i>	Memory Address pointer is out of accepted range
260	<i>P3_FIR_ADDRESS_ERROR</i>	Invalid address
261	<i>P3_FIR_INVALID_ADD_DATA_ERROR</i>	Error flag when addresses of input data and output data are not in range of assigned memory for filter 1--> invalid
262	<i>P3_FIR_INVALID_SAMPLES_NUMBER_ERROR</i>	Error flag when number of samples less than number of taps, operation will not start until number of samples >= number of taps, 1--> invalid
263	<i>P3_FIR_INVALID_ADD_COEFF_ERROR</i>	Error flag when addresses of coeff are not in range of assigned memory for filter 1--> invalid
264	<i>P3_FIR_ACC1_SAT_ERROR</i>	Saturation flag for accumulator 1 , 1 → Saturation
265	<i>P3_FIR_ACC2_SAT_ERROR</i>	Saturation flag for accumulator 2 , 1 → Saturation
266	<i>P3_FIR_ACC3_SAT_ERROR</i>	Saturation flag for accumulator 3 , 1 → Saturation
267	<i>P3_FIR_ACC4_SAT_ERROR</i>	Saturation flag for accumulator 4 , 1 → Saturation
268	<i>P3_LIN_INTRP_XNEW_ACC_SAT_ERROR</i>	Error indicates the saturation of the accumulated Xnew generated internally
269	<i>P3_LIN_INTRP_XNEW_THRES_SAT_ERROR</i>	Error indicates the saturation of Xnew generated internally as being equal to or exceeding the saturation threshold
270	<i>P3_LIN_INTRP_XNEW_LD_MEM_NON_MON_ERROR</i>	Error indicates that the Xnew loaded from memory isn't increasing/decreasing in a monotonic way
271	<i>P3_LIN_INTRP_XNEW_OUT_STRTXOLD_RNG_ERROR</i>	Error indicates that Xold(i)>Xnew and Xold(i+1)>Xnew
272	<i>P3_LIN_INTRP_XNEW_OUT_FNLXOLD_RANGE_ERROR</i>	Error indicates that

	<i>RROR</i>	no more Xold data to be loaded while $Xold(i) < Xnew$ and $Xold(i+1) < Xnew$
273	<i>P3_LIN_INTRP_XOLD_NON_MONO_ERROR</i>	Error Indicates that Xold isn't increasing/decreasing in a monotonic way
274	<i>P3_LIN_INTRP_ZERO_DIV_ZERO_ERROR</i>	Error indicates dividing zero by zero which means $Xold(i+1) = Xold(i) = xnew$
275	<i>P3_LIN_INTRP_SCALR_DIV_ZERO_ERROR</i>	Error indicates divide by zero in scalar division mode
276	<i>P3_LIN_INTRP_WR_XNEW_ERR_ERROR</i>	Error indicates Flag xnew is gated from being written to the memory as its length exceeds 32 bit
277	<i>P3_LIN_INTRP_DMA_ADDR_WRD_ALGN_ERROR</i>	Error indicates that one of the given addresses isn't word aligned (the least 2 LSB $\neq 0$)
278	<i>P3_LIN_INTRP_DMA_ADDR_LSB_IN_RNG_ERROR</i>	Error Indicates LSB of one of given addresses is out of the given address space for the HW Accelerator (greater than or equal $\times 5800$)
279	<i>P3_LIN_INTRP_DMA_ADDR_MSB_IN_RNG_ERROR</i>	Error indicates MSB of one of given addresses is out of the given address space for the HW Accelerator (not equal $\times 200$)
280	<i>ACTION_ABORTED</i>	Error occurred during ISR abort operation
281	<i>USERINTERFACE_DMA_WRITE_ERROR</i>	Error occurred during DMA write operation
282	<i>USERINTERFACE_WRONG_OPERATION</i>	Error occurred during read a wrong operation
283	<i>WDT_WRITE_LOCK_FAILED</i>	Error occurred during write lock
284	<i>WDT_WRITE_UNLOCK_FAILED</i>	Error occurred during write unlock
285	<i>DSP_INITIALIZATION_CONFIGURATION_FILES_IS_EMPTY_ERROR</i>	Error occurred during DSP missing configuration data
286	<i>DSP_INITIALIZATION_CONFIGURATION_FILES_LENGTH_NOT_VALID_ERROR</i>	Error occurred during DSP initialization

		configuration length is not valid
287	<i>DSP_INITIALIZATION_INVALID_INTERFEROGRAM_TYPE_ERROR</i>	Error occurred during DSP initialization for invalid interferogram type
288	<i>DSP_INTERPOLATION_LINEAR_INPUT_SIZE_ZERO_ERROR</i>	Error occurred during DSP interpolation step streaming input size is zero
289	<i>DSP_INTERPOLATION_LINEAR_OUTPUT_SIZE_ZERO_ERROR</i>	Error occurred during DSP interpolation step streaming output size is zero
290	<i>DSP_INTERPOLATION_LINEAR_DIVISION_BY_ZERO_ERROR</i>	Error occurred during DSP interpolation step division by ZERO
291	<i>DSP_MATH_DIVISION_BY_ZERO_ERROR</i>	Error occurred during DSP mathematical division by ZERO operation
292	<i>DSP_Spline_NO_POINTS_ERROR</i>	Error occurred during DSP spline function no of points is not correct
293	<i>DSP_SPLINE_KNOTS_DECREASING_ERROR</i>	Error during DSP Spline cubic operation
294	<i>DSP_SPLINE_UNKNOWN_ERROR</i>	Error occurred during DSP spline for unknown reason
295	<i>DSP_FFT_NO_POINTS_ERROR</i>	Error occurred during DSP FFT number of points is not correct
296	<i>DSP_NOISE_LEVEL_ERROR</i>	Error occurred during DSP noise level problem

Table 3: p3AppManagerStatus values

4. Sequence diagrams

4.1. Initialization

The initialization scenario should be run at least once for the connected NeoSpectra module. The scenario consists of the following steps:

1. Construct the p3AppManager.jar through calling p3AppManagerImpl()
2. Add your class as an observer to be notified by the p3AppManager when asking for an asynchronous action
3. Board initialization through calling InitializeCore()
4. Waiting for finishing initialization
5. Your class will be notified when module initialization is finished




Figure 1: Initialization Sequence

4.2. Interferogram & PSD Run

The Interferogram & PSD scenario consists of the following steps:

1. Start the run procedure through calling runInterSpec(RunTime)
2. Waiting for finishing run
3. Your class will be notified when the run is finished
4. Getting the data through calling getInterSpecData()




Figure : Interferogram & PSD Run Sequence



Figure 3: Spectrum Run Sequence

4.3. Spectrum Run

The Spectrum scenario consists of the following steps:

1. Start the background run procedure through calling `runSpec(RunTime, isSample=false)`
2. Waiting for finishing background run
3. Your class will be notified when the background run is finished
4. Start the sample run procedure through calling `runSpec(RunTime, isSample=true)`
5. Waiting for finishing sample run
6. Your class will be notified when the sample run is finished
7. Getting the data through calling `getSpecData()`

4.4. Adding Gain Settings for the Interferogram and Spectrum

Adding new gain settings for the Interferogram/ Spectrum consists of the following steps:

1. Start adjusting the gain using background by calling `runSpecGainAdjBG (RunTime)`
2. Waiting for finishing background run
3. Your class will be notified when the background run is finished
4. Get the new gain settings by calling `getGainAdjustSpecData ()`
5. To restore the default gain settings from the module, call the function `restoreDefaultSettings()`




Figure 4: Interferogram Gain Adjustment

4.5. Perform Correction

Correction can be done using one of two techniques:

4.5.1. Perform Self-Correction

1. Start the correction using `runCalibCorr()` with a background reading
2. Wait for finishing background run




Figure 4: Self Correction

4.5.1. Perform Correction Using a Standard Sample

1. Start the first step of correction using `wavelengthCalibrationBG()` with a background reading
2. Wait for finishing background run
3. Start the second step of the correction using `wavelengthCalibration()` with a sample reading
4. Wait for finishing the sample run




Figure 5: Correction Using Standard Sample